

Product Specification Sheet



10KVA 3-Phase Power and Lighting Transformer

- 10kVA Continuously rated 3Phase Site Transformer
- Input: 400 Volts 3 Phase 50/60 Hz Delta
- Output: 110V AC
- Vector Group: DYN11
- Output Sockets: 2x32Amp & 4x16Amp Individually protected by Schneider 32A & 16A 2P MCB's
- Lighting Circuits: 2 x 16Amp Individually protected by 16A 2P MCB's
- Incoming Protection: 1 x Schneider 3P 20Amp 'D' Curve MCB
- Enclosure: Powder Coated Sheet Steel rated to IP44 C/W welded up-right handles
- Commando appliance input available (additional charge)



16-02-2026 | 10:58:15

EL-BJÖRN UK Ltd

Unit 5 Beacon Hill Logistics Park, Beacon
Hill Road, Church Crookham,
Fleet, Hampshire, GU52 8DY
Phone: (+44) 01483 729 348
E-mail: info@elbjorn.com

EL-BJÖRN The company name 'EL-BJÖRN' is written in a large, bold, white sans-serif font. To the right of the text is the same stylized lightbulb logo as the page header.

Product Benefits

- 10kVA Continuously rated 3Phase Site Transformer
- Output Sockets: 2no 32Amp & 4no 16Amp Individually protected by Schneider 32A & 16A 2P MCB's
- IP44 Protection Rating
- Enquire for full information

Technical Data

Product name	10KVA 3-Phase Power and Lighting Transformer
Product Number	TRANS002
Input	400 Volts 3 Phase 50/60 Hz Delta
Output	110V AC
Output Sockets	2no 32Amp & 4no16Amp Individually protected by Schneider 32A & 16A 2P MCB's
Lighting Circuits	2no 16Amp Individually protected by 16A 2P MCB's
Incoming Protection	1no Schneider 3P 20Amp 'D' Curve MCB
Vector Group	DYN11

16-02-2026 | 10:58:15



EL-BJÖRN UK Ltd

Unit 5 Beacon Hill Logistics Park, Beacon
Hill Road, Church Crookham,
Fleet, Hampshire, GU52 8DY
Phone: (+44) 01483 729 348
E-mail: info@elbjorn.com

