

# Product Specification Sheet



## 10KVA 3-Phase Power and Lighting Transformer

- 10kVA Continuously rated 3Phase Site Transformer
- Input: 400 Volts 3 Phase 50/60 Hz Delta
- Output: 110V AC
- Vector Group: DYN11
- Output Sockets: 2x32Amp & 4x16Amp Individually protected by Schneider 32A & 16A 2P MCB's
- Lighting Circuits: 2 x 16Amp Individually protected by 16A 2P MCB's
- Incoming Protection: 1 x Schneider 3P 20Amp 'D' Curve MCB
- Enclosure: Powder Coated Sheet Steel rated to IP44 C/W welded up-right handles
- Commando appliance input available (additional charge)



04-07-2026 | 18:06:08

### EL-BJÖRN UK Ltd

Unit 5 Beacon Hill Logistics Park, Beacon Hill Road, Church Crookham, Fleet, Hampshire, GU52 8DY  
Phone: (+44) 01483 729 348  
E-mail: info@elbjorn.com



## Product Benefits

- 10kVA Continuously rated 3Phase Site Transformer
- Output Sockets: 2no 32Amp & 4no 16Amp Individually protected by Schneider 32A & 16A 2P MCB's
- IP44 Protection Rating
- Enquire for full information

## Technical Data

<b>Product name</b>	10KVA 3-Phase Power and Lighting Transformer
<b>Product Number</b>	TRANS002
<b>Input</b>	400 Volts 3 Phase 50/60 Hz Delta
<b>Output</b>	110V AC
<b>Output Sockets</b>	2no 32Amp & 4no16Amp Individually protected by Schneider 32A & 16A 2P MCB's
<b>Lighting Circuits</b>	2no 16Amp Individually protected by 16A 2P MCB's
<b>Incoming Protection</b>	1no Schneider 3P 20Amp 'D' Curve MCB
<b>Vector Group</b>	DYN11

04-07-2026 | 18:06:08

### EL-BJÖRN UK Ltd

Unit 5 Beacon Hill Logistics Park, Beacon Hill Road, Church Crookham, Fleet, Hampshire, GU52 8DY  
Phone: (+44) 01483 729 348  
E-mail: info@elbjorn.com

